



radwag.com



WLC 0.2.X7上皿天秤

WL-227-0001

More information on the website
mirror.radwag.com/ja/info,w1,ARZ



The drawings, photos and graphics used are for illustrative purposes only.

機能

Autotest	Dosing	Plus/Minus Control	Percent Weighing
Parts counting	Peak hold	Formulation	Newton unit measurement
Statistics	Checkweighing	IR sensors	GLP Procedures
Animal weighing	Density determination	Ambient conditions monitoring	Replaceable unit
Statistical Quality Control	ALIBI Memory	Mass for titrator	Wi-Fi

データシート

計測パラメータ

最大ひょう量 [Max]	0,2 kg
最小表示 [d]	0,001 g
法定計量時の単位 [e]	-
風袋範囲	-0,2 kg

計測パラメータ	
繰返し性	0,0014 g
直線性	±0,003 g
安定化時間	2 s
調整	外部、天秤のレベルから (着脱式アダプター)
物理的パラメータ	
レベリングシステム	手動
ディスプレイ	7" セル サンプル 赤外線式
計量皿寸法	ø100 mm
梱包寸法 幅x奥行x高さ	490×400×520 mm
正味重量	1,8 kg
総重量	5,5 kg
工事中	
保護クラス	IP 43
コンポーネントとソフトウェア	
データベース容量	Radwag ASCII プロトコル
通信インターフェース	
通信インターフェース	2×RS232 ¹ , USB-A, USB-B, Ethernet, Wi-Fi
電気的パラメータ	
電源	(ベース, ボトムリング, ガラス容器, ピペット校正アダプタ, エバポレーションリング, 計量皿, ガラス製のフタ, 機械式開閉カバー, 保護用ネジ): 100 – 240V AC 50/60Hz 0,6A; 12V DC 1,2A ミクロ天秤: 10 – 15VDC 0,6A max
環境条件	
動作温度	+10 – +40 °C

* Wi-Fi® is a registered trademark of Wi-Fi® Alliance.



アクセサリ (Additional Fee)

防振台
電源アダプタ
RS 232 ケーブル (はかり - プリンタ)
シガーライターソケット電源ケーブル
USB cable (はかり - プリンタ)
バーコードスキャナ

底部吊り下げ計量
RS 232、RS 485 ケーブル
ディスプレイ
レシートプリンタ
RS 232 – RS 485 コンバータ

ソフトウェア (Additional Fee)

- RAD Key [WX-010-0005]
- R-Lab [WX-010-0080]
- RADWAG Development Studio [WX-010-0104]

- Alibi Reader [WX-010-0114]
- Scale Editor 2.1 [WX-010-0173]

デバイスの寸法 幅x奥行x高さ

