



More information on the website  
[mirror.radwag.com/us/info,w1,ASO](http://mirror.radwag.com/us/info,w1,ASO)















# C32.20.PM Precision Balance

WL-223-0079



The drawings, photos and graphics used are for illustrative purposes only.

## Functions

-  Labelling
-  Plus/Minus Control
-  Percent Weighing
-  Totalizing
-  Parts counting
-  Newton unit measurement
-  Statistics
-  IR sensors
-  Under-pan weighing
-  GLP Procedures
-  Animal weighing
-  Density determination
-  Replaceable unit
-  ALIBI Memory

## Datasheet

Metrological parameters	
Maximum capacity [Max]	20 kg
Minimum load	-
Preload range	2 kg
Readability [d]	0,01 g
Tare range	-20 kg
Minimum weight (USP)	8,2 g

<b>Metrological parameters</b>	
Minimum weight (U=1%, k=2)	0,82 g
Repeatability (Max)	0,02 g
Repeatability (5% Max)	0,0041 g
Linearity	±0,03 g
Stabilization time	1,5 s
Adjustment	internal (automatic)
OIML Class	-
<b>Physical parameters</b>	
Leveling system	manual
Display	5" graphic colour
Weighing pan dimensions	200×185 mm
Packaging dimensions W x D x H	520×520×280 mm
Net weight	11,3 kg
Gross weight	13 kg
<b>Construction</b>	
Protection class	IP 43
<b>Communication interface</b>	
Communication interface	2×RS232, USB-A, USB-B, Ethernet, 4 IN / 4 OUT (digital), Wi-Fi
<b>Electrical parameters</b>	
Power supply	100 - 240 V AC 50 / 60 Hz
Power consumption max.	0,5 A
<b>Environmental conditions</b>	
Operating temperature	+10 – +40 °C

\* Wi-Fi® is a registered trademark of Wi-Fi® Alliance.



## Accessories (Additional Fee)

### Displays

Antivibration tables

Power Adapters

RS 232 cables (scale - printer)

Cigarette lighter receptacle power supply cables

Professional Weighing Tables

### Barcode scanners

Under-pan weighing

RS 232, RS 485 cables

Stands, wall mounting kits and mounting brackets

Receipt Printer

AP2-1 Current Loop Unit

## Software (Additional Fee)

• E2R Weighing [WX-010-0099]

• Label Editor R02 [WX-010-0094]

• Scale Editor - EWAG 2.1 [WX-010-0173]

• RAD Key [WX-010-0005]

• Alibi Reader PC Software [WX-010-0114]

• RADWAG Development Studio [WX-010-0104]

## Device dimensions W x D x H

